MODEL CG300 NEW CAPACITANCE LEVEL MEASURMENT



Features


- Easy operation, easy programming
- dK correction
- Improved buildup insensitivity
- High accuracy operation
- Suitable for a wide range of materials
- LCD for operation status indication

General Description

Model CG300 of integral type is designed for continuous level measurement of liquids or chemicals. This sensor adapts the principle of phase detection and ensures the wide range of sensitivity adjustment, insensitive to buildup, and easy adjustment using digital signals. This sensor can detect Kerosene and Water without changing the circuit board. Model CG300 is not affected by the resistance of buildup due to the phase detection. However, if it is affected, CG300 automatically select reasonable data, and output the signal correctly. When the medium inside of tank is changed, CG300 automatically calculates and output ZERO and SPAN values with one given point adjusted.

Operational Description


The basic oscillator circuit is of the parallel resonance circuit with L (coil) and C (capacitance between the electrodes). The oscillation frequency (f) of this circuit is: $f=1/2\pi\sqrt{LC}$. The frequency without material around the sensor (f1) is: $f1=1/2\pi\sqrt{LC}$, where C is the capacitance without material around the sensor (ZORO point). With material around the sensor, the capacitance increases (C+ Δ C), and the frequency (f2) is: $f2=1/2\pi\sqrt{L}(C+\Delta C)$, where $C+\Delta C$ is the capacitance with material around the sensor (SPAN point). The sensor detects the frequency change from f1, and gives output (4 to 20mA) corresponding to the change. With the incorporated microcomputer, offset of output current and reversed output signals for ZERO/SPAN points are also available.




- Dielectric constant compensation function
 When the dielectric constant of medium changes,
 the conventional products need re-adjustment
 of Zero and Span points. Model CG300
 automatically calculates and output Zero and
 Span values with one given point adjusted.
- Wide range of measuring mediums
 Successful operation for measured medium of 30 to 2000 pF

Example of medium

Name	Dielectric Constants	
Kerosene	2.8	
Ammonia	15-25	
Isobutyl Alcohl	18.7-31.7	
Methyl Alcohol	33-56.6	
Water	48-80	





Specifications

Specification Model	Integral	CG300N	CG300F	
	Separation	CG300BN	CG300BF	
Drawing		1122) Hex.41 Hex.41 10.02 S1 139)	φ114 (76) φ105 φ105 φ15×t22 (66) φ15×t22 (67) φ15×t22 (67) φ15×t22 (68) φ105 (68) φ105 (68) φ105 (68) (68) φ105 (68)	
Туре		Stan	 Standard	
Mounting		R1	R1 JIS5K50A	
Supply Power		100 to 240V AC	100 to 240V AC ±10%, 50/60Hz	
Power Consumption		Integral type: Approx. 7VA Max., Separation type Approx. 6VA Max.		
Output Signal		4 to 20mA DC		
Load Resistive				
Operating	Housing	-25 to 65°C		
Temperature	Electrode	-10 to 60°C		
Maximum Pressure		100 kPa Max. (Except mounting part) 85% RH Max.		
Maximum Humidity85% RH Max.Sensitivity30 to 2000 pF				
Accuracy		±0.5% F.S.		
Material	Housing	±0.5 % F.S. ADC12		
	Electrode 304SS			
	Insulation tube	PFA		
	O-ring		/FKM	
	Radiation fin	·		
Maximum Probe Length		4000mm		
Cable Entry		G3/4		
Protection		Housing: IP65 / Electrode: IP68		
Recommended cable Power supply: IV 2 x 2.0mm² or CVV 2.0mm² x 2C Output signal / Between sensor and controller: CVV-S 1.25mm².				

^{*}S1 and S2 on the drawing is blanking zone.

CG300NT	CG300FT	0014400		
CG300BNT	CGM300BFT	CGM1100		
φ114 (76) φ130 φ15×12 20 0 X	φ114 (76) φ130 φ15×12 α α α α α α α α α α α α α α α α α α α	67 83 08E		
Heat	Proof	Controller		
R1	JIS5K50A	Controlled		
100 to 240V AC ±10%, 50/60Hz				
Integral type: Approx. 7VA Max., Separation type Approx. 6VA Max.				
	4 to 20mA DC			
600 Ω Max. -25 to 65°C -1		-10 to 60°C		
-25 to 65 C -10 to 130°C		-10 10 00 0		
100 kPa Max. (Except mounting part)				
85% RH Max.				
30 to 2000 pF				
±0.5% F.S.				
ADC12		SPCC		
304SS				
PFA				
FPM/FKM				
	ISS			
4000				
GG		IDOO		
Housing: IP65 / Electrode: IP68		IP20		
Power supply: IV 2 x 2.0mm² or CVV 2.0mm² x 2C Output signal / Between sensor and controller: CVV-S 1.25mm² x 2C		Separation distance 200m Max.		
	*S1 and S2 on the drawing is blanking zone.			

^{*}S1 and S2 on the drawing is blanking zone.